



Artikel-Nr.: 4699
Hersteller: Kramer AV

MC3-2F-2F

€ 832,50 *

zzgl. MwSt. [zzgl. Versandkosten](#)
Lieferzeit ca. 5 Tage

Produktinformationen "MC3-2F-2F"

4K60 Fiber Optic 2xIN + 2xOUT Card

- High Resolution Audio–Visual Experience Modular matrix card supports high 4K60 4:4:4 HDMI signal distribution from and towards any input and output port of the modular matrix. Near–zero latency video chroma sub–sampling conversion technology is employed to auto–adapt above 10G HDMI signals to 10G optical link signal data–rate.

- Flexible Standard Fiber Extender HDMI fiber extender for ultra–reach signals distribution over either multi–mode or single–mode optical fiber infrastructures, using Kramer SFP+ pluggable optical modules (multi–mode SFP+ included).

Note: To ensure specified performance, support, and warranty of this product, use only Kramer's certified hi–performance SFP+ pluggable optical modules.

- Multi–drop Signal Distribution Use optical splitters to extend the input signals from a single transmitter to multiple receivers, for displaying the same content on multiple display devices using optical splitting only, with no need for AV distribution amplifiers.

- HDMI Signal Extension HDCP 2.2 compliant and supports up to 18G (6G per channel) data rate, LPCM 7.1, Dolby True HD, and DTS–HD as specified in HDMI 2.0.

- Bidirectional RS–232 Extension Serial interface data flows end–to–end in both directions, to enable data transmission and control of devices.

- I–EDIDPro™ Kramer Intelligent EDID Processing™ Intelligent EDID handling, processing and pass–through algorithm that ensures Plug and Play operation for HDMI source and display systems.

- Cost–Effective Maintenance Fiber link connection LED indications facilitate easy local troubleshooting.

- Produktabmessung: 25.50cm x 13.00cm x 2.00cm (10.04 x 5.12 x 0.79) W, D, H

- Versandabmessung: 29.20cm x 16.50cm x 6.00cm (11.50 x 6.50 x 2.36) W, D, H

- Produktgewicht: 0.3kg (0.6lbs) approx.

- Versandgewicht: 0.4kg (0.9lbs) approx.

Gebrauchsanleitung:

[Gebrauchsanleitung MC3-2F-2F](#)

Weiterführende Links zu"MC3-2F-2F"

- [- Fragen zum Artikel?](#)

- [- Weitere Artikel von Kramer AV](#)